

LX Series Headset - LX06



Lightweight Headset with PTT

- Single sided lightweight headset designed to provide highly intelligible communication for dispatch, command centres and a variety of other applications.
- Use as an accessory to a handheld or mobile radio. Cord termination allows this connection via an SED adapter cord.
- Continuous height adjustment makes for a comfortable fit.
- Foam ear cushion ensures maximum comfort.
- Dynamic Gooseneck boom microphone provides optimal flexibility, allowing the wearer to adjust the microphone precisely to their preference.
- Microphones can be installed on the left or right.
- Quick disconnect termination.
- Inline PTT switch.
- Load bearing clothing clip.

| Earphone | Lightweight, Single Receiver | |
|-----------------|---|--------------------------------------|
| | Impedance : | 150 Ohms |
| | Frequency Response: | 100 to 5000 Hz |
| | Sensitivity @ 1 KHz: | 72.5 dB 103 ± 4 dBv |
| Microphone | Dynamic Noise Canceling Gooseneck boom microphone | |
| | Ambient Noise: | Recommended in noise levels to 80 dB |
| | Frequency Response: | 200 to 5000 Hz |
| | Sensitivity: | -640 ± 4 dBv |
| | Impedance @ 1 kHz: | 200 Ohms |
| Connection Cord | | |
| | Connector: | Nexus quick disconnect |
| | Cord: | 43", straight |