

LX Series Headset - LX111



Lightweight Headset

- Single sided lightweight headset designed to provide highly intelligible communication for dispatch, command centres and a variety of other applications.
- Use as an accessory to a handheld or mobile radio. Cord termination allows this connection via an SED adapter cord.
- Continuous height adjustment makes for a comfortable fit.
- Replaceable ear cushions ensure the best comfort possible and a longer life span of the headset.
- Dynamic Gooseneck boom microphone provides optimal flexibility, allowing the wearer to adjust the microphone precisely to their preference and comfort.
- Microphones can be installed on the left or right.
- Quick disconnect termination.
- Load bearing clothing clip.

Earphone	Lightweight, Single Receiver	
	Impedance :	150 Ohms
	Frequency Response:	100 to 5000 Hz
	Sensitivity @ 1 KHz:	72.5 dB 103 ± 4 dBv
Microphone	Dynamic Noise Canceling Gooseneck boom microphone	
	Ambient Noise:	Recommended in noise levels to 80 dB
	Frequency Response:	200 to 5000 Hz
	Sensitivity:	-640 ± 4 dBv
	Impedance @ 1 kHz:	200 Ohms
Connection Cord		
	Connector:	Nexus quick disconnect
	Cord:	7' , straight